

1200W切割灯通道表 (41CH)

通道1	名称	数值	描述		
CH1	频闪	0-19	关光		
		20-24	开光		
		25-64	由慢到快频闪		
		65-69	开光		
		70-84	由慢到快渐变频闪1		
		85-89	开光		
		90-104	由慢到快渐变频闪2		
		105-109	开光		
		110-124	由慢到快渐变频闪3		
		125-129	开光		
		130-144	由慢到快随机频闪		
		145-255	开光		
		CH2	调光	0-255	0-100%调光
		CH3	调光微调	0-255	
CH4	C	0-255			
CH5	微调	0-255			
CH6	M	0-255			
CH7	微调	0-255			
CH8	Y	0-255			
CH9	微调	0-255			
CH10	CTO	0-255			
CH11	微调	0-255			
CH12	颜色	0-5	白光		
		6-11	颜色1		
		12-17	颜色2		
		18-23	颜色3		
		24-29	颜色4		
		30-35	颜色5		
		36-41	颜色6		
		42-47	颜色7		
		48-127	线性颜色		
		128-190	由快到慢正向流水		
		191-192	停止		
		193-255	由慢到快反向流水		
CH13	旋转图案	0-6	白光		
		7-13	图案1		
		14-20	图案2		
		21-27	图案3		
		28-34	图案4		
		35-41	图案5		
		42-55	图案6		
		56-62	由慢到快抖动图案1		
		63-69	由慢到快抖动图案2		
		70-76	由慢到快抖动图案3		
		77-83	由慢到快抖动图案4		
		84-90	由慢到快抖动图案5		
		91-104	由慢到快抖动图案6		
		105-179	由快到慢正向流水		
		180-191	停止		
		192-255	由慢到快反向流水		
CH14	图案自转	0-127	0-400度		
		128-190	由快到慢正向流水		
		191-192	停止		
		193-255	由慢到快反向流水		
CH15	自转微调	0-255			
		0-6	白光		
		7-13	图案1		
		14-20	图案2		
		21-27	图案3		

H13	李	
H1	果	
H2	1	
H2	2	
H2	3	
H2	4	
H2	5	
H2	6	
H2	7	
H2	8	
H2	9	
H2	10	
H2	11	
H2	12	
H2	13	
H2	14	
H2	15	
H2	16	
H2	17	
H2	18	
H2	19	
H2	20	
H2	21	
H2	22	
H2	23	
H2	24	
H2	25	
H2	26	
H2	27	
H2	28	
H2	29	
H2	30	
H2	31	
H2	32	
H2	33	
H2	34	
H2	35	
H2	36	
H2	37	
H2	38	
H2	39	
H2	40	
H2	41	
H2	42	
H2	43	
H2	44	
H2	45	
H2	46	
H2	47	
H2	48	
H2	49	
H2	50	
H2	51	
H2	52	
H2	53	
H2	54	
H2	55	
H2	56	
H2	57	
H2	58	
H2	59	
H2	60	
H2	61	
H2	62	
H2	63	
H2	64	
H2	65	
H2	66	
H2	67	
H2	68	
H2	69	
H2	70	
H2	71	
H2	72	
H2	73	
H2	74	
H2	75	
H2	76	
H2	77	
H2	78	
H2	79	
H2	80	
H2	81	
H2	82	
H2	83	
H2	84	
H2	85	
H2	86	
H2	87	
H2	88	
H2	89	
H2	90	
H2	91	
H2	92	
H2	93	
H2	94	
H2	95	
H2	96	
H2	97	
H2	98	
H2	99	
H2	100	